



Correspondance des valeurs midi du paramètre "TIME" (CC90) en valeur BPM des moteurs d'effet delay du Yamaha Reface CP :

Midi value	D.Delay BPM	A.Delay BPM	Midi value	D.Delay BPM	A.Delay BPM	Midi value	D.Delay BPM	A.Delay BPM	Midi value	D.Delay BPM	A.Delay BPM
0	ind	ind	32	220	244	64	108	99	96	58,5	61
1	ind	ind	33	214	232	65	105	98	97	57,5	60
2	ind	ind	34	208	226	66	102,5	97	98	56,5	60
3	ind	ind	35	202	220	67	100	95	99	56	58
4	ind	ind	36	196,5	214	68	97,5	95	100	55,5	58
5	ind	ind	37	191,5	208	69	95,5	92	101	54,5	56
6	ind	ind	38	186,5	202	70	93	92	102	53,5	56
7	ind	ind	39	182	197,5	71	91	90	103	53	55
8	ind	ind	40	177,5	192	72	89	87	104	52	54
9	ind	ind	41	173,5	187	73	87	87	105	51,5	54
10	ind	ind	42	169,5	182	74	85,5	85	106	51	52
11	ind	ind	43	165,5	177	75	83,5	85	107	50,5	52
12	ind	ind	44	162	172,5	76	82	83	108	50	51
13	ind	ind	45	158,5	167,5	77	80	83	109	49	51
14	ind	ind	46	155	162	78	78,5	80	110	48,5	49
15	ind	ind	47	152	159	79	77	78	111	48	48
16	ind	ind	48	149	150	80	76	78	112	47,5	48
17	ind	ind	49	146	146	81	74,5	76	113	47	47
18	ind	ind	50	143	142	82	73	76	114	46,5	47
19	ind	ind	51	140,5	139	83	72	74	115	46	46
20	343	ind	52	137,5	135	84	70,5	74	116	45,5	46
21	328	ind	53	134	131,5	85	69	72	117	45	44
22	314	ind	54	132,5	128	86	68	72	118	44,5	44
23	301	314	55	130	124	87	67	70	119	44	43
24	289	305	56	128	121	88	66	68	120	43,5	42
25	278	298	57	126	118	89	65	68	121	43	42
26	268	289	58	124	115	90	64	66	122	42,5	41
27	259	280	59	121,5	112	91	63	66	123	42	41
28	250	263	60	120	109	92	62	64	124	41,5	40
29	242	266	61	118	106	93	61	64	125	41	40
30	234	263	62	116	103	94	60	63	126	40,5	39
31	227	260	63	111	100	95	59	63	127	40	37,5

MIDI



D. DELAY



A. DELAY

